

SNSY-A2000-036

UNITED STATES PATENT APPLICATION FOR

SYSTEM AND METHOD FOR

AUTOMATICALLY RETARGETING TEST

VECTORS BETWEEN DIFFERENT TESTER TYPES

Inventors:

Rohit Kapur

and

Thomas Williams

Prepared by:

WAGNER, MURABITO & HAO LLP

Two North Market Street

Third Floor

San Jose, California 95113

(408) 938-9060 Voice

(408) 938-9069 Facsimile

SYSTEM AND METHOD FOR  
AUTOMATICALLY RETARGETING TEST  
VECTORS BETWEEN DIFFERENT TESTER TYPES

RELATED US APPLICATION

5           This patent application claims priority to US provisional patent application, serial number 60/229,653, filed August 31, 2000, entitled "Tester Retargetable Patterns," by Kapur et al.

FIELD OF THE INVENTION

10           The field of the present invention pertains to the testing of integrated circuits using automated testing equipment (ATE). More particularly, the present invention pertains to a method and system for efficiently allowing testers of various pin capacities to apply the same set of test vectors that were designed for a high pin capacity tester.

15

BACKGROUND OF THE INVENTION

Computer systems and electronic devices are continually growing in capability and complexity. The size and complexity of integrated electronic systems are likewise increasing, making it critical that the component parts of

20 these systems operate without fault. This requires that each component, or integrated circuit "chip," be rigorously tested before it is sold. However, as integrated circuit chips become more powerful, the methods and systems

required to detect flaws within them become increasingly sophisticated and expensive.

Integrated circuit designs have become more complex in part because  
5 they are made more dense. As a result, they have become progressively  
harder to test in order to ensure correct and complete functionality. Higher  
densities are achieved in part by reducing the amount of space between  
transistors and other components which comprise the integrated circuit. As  
such, the "place and route" tolerances for the integrated circuit are reduced, and  
10 the potential for introducing fabrication errors and introducing structural faults in  
the circuit increases. Additionally, the complicated placement of the internal  
structure and nature of the defects encountered in such high density integrated  
circuits requires the use of sophisticated algorithms in order to ensure adequate  
defect detection, e.g., being able to determine whether structural defects  
15 between the closely spaced gate elements, such as a bit short, broken link, or  
the like, exist. Hence, the testing cost can be very significant for the latest and  
largest high density integrated circuits.

Very sophisticated test programs, called automatic test pattern  
20 generation (ATPG) programs, are used to analyze the integrated circuit designs  
and generate therefrom test patterns (e.g., also referred to as test programs or  
test vectors) used for testing the devices in ATE systems. The objective of the  
ATPG program is to generate an accurate, high defect coverage test pattern as  
efficiently as possible, to reduce the cost. As a result of analyzing the target  
25 design, the ATPG tool determines a stimulus for all the accessible points of the

target design. During chip verification, this stimulus is applied by the tester to the integrated circuit and the real time response of the chip is compared with the pre-computed response of the test pattern.

5           As discussed above, testing systems, or "testers" are used to apply test vectors to a device under test, capture the test results and shift them out for examination and comparison. However, as with any resource, test facilities have testers of different capabilities and configurations. The testers differ in their clocking characteristics, their power supply capabilities, their memory  
10 resources used behind each pin, and most importantly, they differ in the number of pins that can supply and receive scan data and functional inputs/outputs, etc. Typically, the more pins available on a tester, the more expensive the tester equipment. For example, today testers cost approximately \$5,000.00 per pin supported. The more pins the tester can drive, the more scan  
15 chains a design can implement. The more scan chains available, the shorter the scan chains can be, thereby reducing the time it takes to load them up. Conversely, a tester with few pins only supports a design having fewer but longer scan chains. Therefore, testers with high pin count can drive many scan chains and the more scan chains available, the shorter they can be, the faster  
20 they load and the more economical the test.

Figure 1A illustrates an integrated circuit device 18 having fewer external pins, but larger sized scan chains 12a-12d. Scan chains, as are well known, contain scan cells (sequential elements) coupled in series. Because pin count  
25 is restricted, only a few scan chains can be accommodated, so they are longer.

The reduced number of scan chains require fewer numbers of scan-in pins 14 and scan-out pins 16. Unfortunately, the longer scan chains require more time to scan-in and scan-out their data. This leads to a low performance, low pin count, testing environment. The test vectors developed for this system are also longer and incompatible with high performance testers. ATPG processes that generate long test vectors are used for lower performance testers. Figure 1D illustrates a low performance, low pin count, tester 40 applied to a device under test 44. The device 44 is placed into a multi-pin socket 46 which connects to the low pin interface 42.

10

Figure 1B illustrates an integrated circuit device 26 having many external pins and shorter scan chains 20i. Because the scan chains are shorter, there are many of them and they require high numbers of scan-in pins 22 and scan-out pins 24. The test vectors are also shorter and incompatible with low performance testers. The shorter scan chains 20i require less time to scan-in and scan-out their data and this leads to a high performance, higher pin count, testing environment. This discussion assumes the scan rates are equal. ATPG processes that generate many short test vectors are used for high performance testers. Figure 1C illustrates a high performance, high pin count, tester 30 applied to a device under test 34. The device 34 is placed into a multi-pin socket 36 which connects to the high pin interface 32.

15

20

25

Although testers vary in pin capacity, nevertheless, the test data generated by ATPG processes is typically generated in an environment that is oblivious to the tester capabilities. For example, in many cases, test patterns

tend to be routinely developed for high performance testers without knowing the capabilities of the test facility. This is done because most test engineers are geared to reduce test application time. However, to limit costs, a test facility typically acquires some low cost testers and some high cost testers, which differ

5 in the number of full functional pins they have. If a test facility (e.g., having a mix of both high and low capacity testers) receives test vectors developed for high performance testers, the result will be that many of their low cost testers are left idle because of test vector incompatibility. Having any of these testers idle is a waste of resources and money. It would be advantageous, then, to provide a

10 system that can make full use of the various different types of testers that a facility has but is based on a single set of developed test vectors.

## SUMMARY OF THE INVENTION

Accordingly, the present invention provides a system and a method for making full use of the various different types of testers that a test facility has but uses a single set of developed test vectors. The present invention therefore  
5 leverages pin count differences among the testing systems and allows all equipment to be used on the test floor based on a single set of test vectors. The present invention provides a system and method for the dynamic and automatic reconfiguration of test circuitry internal to a chip to change the pin requirements of the data to better match a tester system. In this way, the present invention  
10 allows a single set of test patterns to be retargetable to any tester system (e.g., high or low pin capacity) in order to better utilize expensive testing hardware and therefore save costs in the testing phase of integrated circuit fabrication.

A system and method are described herein for automatically retargeting  
15 a single set of test vectors for application on tester systems having different performance capabilities, e.g., different pin capacities. The system includes a user selectable mode selector that can be adjustable between different test performance modes, e.g., high test mode, medium test mode and low test mode, in one instance. In the high performance test mode, the system allows the  
20 single set of test vectors to be applied efficiently on a high performance test system, e.g., a tester having a high pin count. In the low performance test mode, the same test vectors can be applied but using a low performance test system, e.g., a tester having a low pin count.

By allowing the same set of test vectors to be used in a high performance or a low performance testing environment, a testing facility can make maximum use of its available testing equipment for efficiently testing an integrated circuit device thereby reducing the costs of testing the integrated circuit devices by  
5 reducing the numbers of idle test equipment. The set of test vectors used, in one embodiment, are developed for a high performance test system. The novel system alters the communication protocol used to deliver the test vectors, and the functional inputs, depending on the performance mode selected by the user. However, the test data itself does not change over the different performance  
10 modes. The novel system includes on-chip circuitry that can automatically reconfigure the number and the size of the scan chains within the integrated circuit depending on the performance mode selected. Other techniques and configurations are used for reducing the number of functional input/output pins required to perform a test, while still being able to use test vectors designed for  
15 high performance test systems.

More specifically, an embodiment of the present invention includes an integrated circuit device for communicating with a first tester of a first pin capacity to receive test vectors developed for a second tester of a second pin  
20 capacity, the device comprising: scan chains; and reconfiguration logic coupled to the scan chains and for altering the number of pins required to test the device under test by reconfiguring the individual length and number of the scan chains based on a mode signal, the reconfiguration logic providing compatibility  
between the test vectors and the second tester having the second pin capacity,  
25 the mode signal selecting between the first tester and the second tester.



Another embodiment of the present invention includes an automated testing equipment (ATE) system for testing an integrated circuit device comprising: a storage medium for storing a set of test vectors developed for a tester having a first pin capacity; a user selector selecting modes between a tester having the first pin capacity and a tester having a second pin capacity; and a device under test for coupling with one of the testers to receive the test vectors, the device under test comprising: scan chains; and reconfiguration logic coupled to the scan chains and for altering the number of pins required to test the device under test by reconfiguring the individual length and number of the scan chains based on the user selector, the reconfiguration logic providing compatibility between the test vectors and the tester having the second pin capacity.

## BRIEF DESCRIPTION OF THE DRAWINGS

The present invention is illustrated by way of example and not by way of limitation, in the figures of the accompanying drawings and in which like reference numerals refer to similar elements and in which:

5

Figure 1A illustrates an integrated circuit device having long scan chains and low pin count thereby compatible with a low performance, and therefore a low cost, tester system.

10

Figure 1B illustrates an integrated circuit device having many short scan chains and high pin count thereby compatible with a high performance, and therefore a high cost, tester system.

15

Figure 1C illustrates a high performance tester system having a high pin count (e.g., 1000+ pins) interface coupled to a device under test using a multi-pin socket.

20

Figure 1D illustrates a low performance tester system having a low pin count (e.g., 64+ pins) interface coupled to a device under test using a multi-pin socket.

Figure 2 is a diagram of computer system portion of an automatic test equipment (ATE) system upon which embodiments of the present invention can be practiced.

Figure 3 illustrates a system in accordance with an embodiment of the present invention having a performance mode selector allowing either a high performance test system or a low performance test system to use the same set  
5 of test vectors on a device under test.

Figure 4A illustrates on-chip reconfiguration circuitry, responsive to the mode selector, for reconfiguring the length of the internal scan chains within an integrated circuit device (under test) in accordance with an embodiment of the  
10 present invention.

Figure 4B illustrates another example of on-chip reconfiguration circuitry, responsive to the mode selector, for reconfiguring the length of the internal scan chains within an integrated circuit device (under test) in accordance with an  
15 embodiment of the present invention.

Figure 5 illustrates on-chip reconfiguration circuitry in accordance with an embodiment of the present invention for reconfiguring functional inputs/outputs between a high performance test mode and a low performance test mode.  
20

Figure 6 illustrates a flow diagram of steps performed in accordance with an embodiment of the present invention for a method of applying test vectors developed for a high performance tester but using a low performance tester.

Figure 7A illustrates an exemplary device under test in accordance with the present invention having reconfigurable scan chains and functional input/outputs.

- 5            Figure 7B illustrates pseudo code in accordance with one embodiment of the present invention implementing test sequences for applying a single set of test vectors to either a high performance tester or a low performance tester.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227

## DETAILED DESCRIPTION OF THE INVENTION

Reference will now be made in detail to the embodiments of the invention, a method and system for automatically retargeting test vectors developed for a high performance tester to be applied by either a low  
5 performance tester or a high performance tester based on a mode selector, examples of which are illustrated in the accompanying drawings. While the invention will be described in conjunction with the preferred embodiments, it will be understood that they are not intended to limit the invention to these embodiments. The invention is intended to cover alternatives, modifications  
10 and equivalents, which may be included within the spirit and scope of the invention as defined by the appended claims. Furthermore, in the following detailed description of the present invention, numerous specific details are set forth in order to provide a thorough understanding of the present invention. However, it will be obvious to one of ordinary skill in the art that the present  
15 invention may be practiced without these specific details. In other instances, well known methods, procedures, components, and circuits have not been described in detail as not to obscure aspects of the present invention unnecessarily.

20

## NOTATION AND NOMENCLATURE

Some portions of the detailed descriptions which follow are presented in terms of procedures, steps, logic blocks, processing, and other symbolic representations of operations on data bits within a computer memory, e.g., flow diagram 500 of Figure 6 and the pseudo code of Figure 7B. These descriptions

and representations are the means used by those skilled in the data processing arts to convey most effectively the substance of their work to others skilled in the art. A procedure, computer executed step, logic block, process, etc., are here, and generally, conceived to be self-consistent sequences of steps or

5 instructions leading to a desired result. The steps are those requiring physical manipulations of physical quantities. Usually, though not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated in a computer system. It has proven convenient at times, principally for reasons of  
10 common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely  
15 convenient labels applied to these quantities. Unless specifically stated otherwise as apparent from the following discussions, it is appreciated that throughout the present invention, discussions utilizing terms such as "processing," "computing," "simulating," "translating," "instantiating," "determining," "displaying," "recognizing," or the like, sometimes refer to the  
20 action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data similarly represented as physical quantities within the computer

system registers or memories or other such information storage, transmission, or display devices.

### ATE COMPUTER SYSTEM PLATFORM 112

5 Referring to Figure 2, automatic test equipment (ATE) can contain one or more computer systems for performing automated testing functionality. A computer system 112 is illustrated. Within the following discussions of the present invention, certain processes and steps are discussed that are realized, in one embodiment, as a series of instructions (e.g., software program) that  
10 reside within computer readable memory units of system 112 and executed by processors of system 112. When executed, the instructions cause computer system 12 to perform specific actions and exhibit specific behavior which is described in detail to follow.

15 In general, the system 112 of the present invention includes an address/data bus 100 for communicating information, one or more central processor(s) 101 coupled with bus 100 for processing information and instructions, a computer readable volatile memory unit 102 (e.g., random access memory, static RAM, dynamic RAM, etc.) coupled with bus 100 for  
20 storing information and instructions for the central processor(s) 101, a computer readable non-volatile memory unit 103 (e.g., read only memory, programmable ROM, flash memory, EPROM, EEPROM, etc.) coupled with bus 100 for storing static information and instructions for processor(s) 101.

System 112 of Figure 2 can optionally include a mass storage computer readable data storage device 104, such as a magnetic or optical disk and disk drive coupled with bus 100 for storing information and instructions. Optionally, system 112 can also include a display device 105 coupled to bus 100 for displaying information to the computer user, an alphanumeric input device 106 including alphanumeric and function keys coupled to bus 100 for communicating information and command selections to central processor(s) 101, a cursor control device 107 coupled to bus for communicating user input information and command selections to the central processor(s) 101, and a signal input/output device 108 coupled to the bus 100 for communicating messages, command selections, data, etc., to and from processor(s) 101.

### TESTER RETARGETABLE PATTERNS

Figure 3 illustrates a testing configuration 200 in accordance with an embodiment of the present invention. Configuration 200 allows a single set of test patterns, e.g., test data 230, to be used by either a high performance or a low performance tester 220 in the testing of a device under test 260. In the configuration 200, the device under test 260 is an integrated circuit device that may be mounted in a multi-pin socket 250 that is connected via a multi-pin interface 280 to the tester (either high or low performance) 220. The number of active pins in the multi-pin interface 280 depends on the performance level of the tester being employed to perform the test. In one example, a high performance tester contains 1000 or more active pins in the interface 280 while a low performance tester contains 64 or more active pins in the interface 280.



An active pin represents a pin that resides in the interface connector and is actually used by the tester.

Importantly, the configuration 200 provides a test mode selector 240 that can be user adjustable. The mode selector indicates the performance level of the tester 220 being employed to perform the testing operations. A mode selection signal is then carried over line 270. The mode selection signal line 270 is connected to the device under test 260 and also coupled to a protocol unit 210. Depending on the test mode, the mode signal over line 270 causes on-chip circuitry (in device 260) to reconfigure such that it becomes compatible with testers of different pin capacities. In the example shown in Figure 3, the possible performance mode selections available are low and high, however, based on this example, the configuration 200 can readily be expanded and extended to encompass multiple other discrete performance levels, e.g., low, medium, high, etc.

The protocol unit 210 of Figure 3 contains different communication protocols used for the different performance levels supported. That is to say, while the same test vectors 230 are used for high or low performance testers, the communication protocol that is used to apply these test vectors, and used to acquire the resulting test data, is different depending on the performance level selected by control signal line 270. The communication protocol is often called a "test sequence." Test information is composed of test data 230 and the test sequence. The test sequence contains the operations required to get the test data into the scan chains and apply the test. According to the present invention,

the test data 230 does not need to be changed for the different configurations of the scan chains (discussed more below). However, the test sequence is changed moderately to make the dynamic performance selection possible.

5 In accordance with an embodiment of the present invention, to allow for a flexible number of pins used by the test data, some design for test (DFT) circuitry is put into the device 260 ("on-chip") such that the total pin count required from the tester 220 can be varied. Reconfiguration is provided, in one embodiment, through multiplexers controlled by a few selected pins which indicate the  
10 selected performance mode.

There are three types of input/outputs to the design 260, namely, the control inputs, the scan input/outputs and the functional input/outputs of the design 260. Scan inputs feed scan chains while functional inputs feed  
15 combinational logic. In order to provide a low performance interface, the embodiments of the present invention reconfigure the application of test and other data to utilize a reduce set of pins. While the control inputs are largely not changed, the remaining inputs and outputs (e.g., scan and functional) are reconfigurable to minimize the number of pins needed on the tester. Figure 4A  
20 and Figure 4B illustrate examples of the manner in which the present invention reconfigures the logic on the device 260 in order to vary the number of scan-in and scan-out pins to accommodate different testers. Figure 5 illustrates examples of the manner in which the present invention reconfigures the logic on the device 260 in order to vary the number of functional input and output pins  
25 to accommodate different testers.

Figure 4A illustrates an exemplary device under test 260a including its scan circuitry and certain DFT circuitry 330 added in accordance with the present invention for providing performance reconfiguration. Although the present invention can be applied to numerous configurations of the design, with different pin counts and requirements from the tester, two exemplary configurations are described below with respect to the scan data. In one configuration, a high pin count is used including individual functional inputs and many balanced scan chains for low test application time. Another configuration is discussed that has a very low pin count achieved at the trade-off of higher test application times caused by longer scan chains.

Mux 330 of Figure 4A can be viewed as reconfiguration logic. In this example, two modes of operation are supported, high performance and low performance. Two exemplary scan chains of equal length, L, 310a and 310b are shown. The scan chains are comprised of L number of individual scan cells (e.g., sequential cells) that are coupled in series. Scan chains, scan cells and scan enable signals are described in more detail in the following US Patents which are incorporated herein by reference: US Patent No. 5,696,771, issued December 9, 1997, entitled "Apparatus for Performing Partial Unscan and Near Full Scan within Design for Test Applications," serial number 08/649,788; US Patent No. 5,949,692, issued September 7, 1999, entitled "Hierarchical Scan Architecture for Design for Test Applications," serial number 08/704,129; US Patent No. 5,703,789, issued December 30, 1997, entitled "Test Ready Compiler for Design for Test Synthesis," serial number 08/581,187; and US

Patent 5,903,466, issued May 11, 1999, entitled "Constraint Driven Scan Insertion for Design for Test Applications," serial number 08/581,379.

Each scan chain 310a and 310b has its own scan-in or scan-input 320a and 320b. Each scan chain also has a scan-out or scan output 340a and 340b. The scan-out 340b of scan chain 310b is connected to one input of multiplexer 330. The other input of the multiplexer is coupled to the scan-in 320a. The output of the multiplexer 330 is coupled to the input of the scan chain 310a. A control selector 270a is coupled to the select inputs of the multiplexer (mux) 330. In high performance mode, selector 270a is low and scan data is shifted into the scan chains using both scan-ins 320a and 320b and likewise scan data is shifted out of device 260a using both scan-outs 340a and 340b. In this case, 5 pins are used for scan data. A separate scan vector, S1 and S2, are shifted into each scan chain separately. At least L shift clocks are required to perform this function since the scan chains are L cells long. Simultaneously, test data is shifted out of the scan chains.

However, in low performance mode, line 270a is high. In this mode, scan-in 320a is ignored and also scan-out 340b is ignored. The scan vector S12+S11 (where + is a concatenation operation) is scanned into scan-in 320b, through mux 330 and partially into scan chain 310a. Likewise, the result (SO1+SO2) is scanned out of scan-out 340a. At least 2L shift clocks are required to perform this function since the scan chains are L cells long and, in this mode, they are connected together in series (2L). In this case, only 3 pins

are used for scan data. This is almost a 100 percent savings in pins used to accomplish the same testing operations at an albeit lower performance level.

It is appreciated that this configuration is scalable and that many more  
5 scan chains are typically implemented in device 260a and that scan chains  
310a and 310b are shown for example only. In an typical implementation, the  
scan and mux circuitry would be replicated many times over with all muxes  
having their select lines coupled together to provide the performance  
adjustments.

10

Figure 4B illustrates another exemplary device under test 260b  
configured in accordance with the present invention. In this example, three  
different performance modes of operation are available: high; medium; and low  
and they are implemented using reconfiguration logic 330a-330c and related  
15 connections. In high performance mode, there are four separate scan chains  
(chains 310, 310b, 310c and 310d). In medium performance mode, there are  
two separate scan chains (chain 310a+310b and chain 310c+310d). Lastly, in  
low performance mode, there is one single scan chain (chain  
310a+310b+310c+310d). Like the example of Figure 4A, the configuration of  
20 Figure 4B is scalable and is typically replicated many times over with common  
muxes having the same control lines coupled thereto.

On chip control logic 360 generates the appropriate control signals C0  
and C1 based on the user performance mode selection signal 270b. The

control lines 365 are coupled to each mux 330a-330c in the same fashion.

Table I below illustrates the performance modes versus the control signals:

Table I

5	C0	C1	Performance Level
	0	0	High
	0	1	Medium
	1	0	Low

- 10 When in high performance mode, all scan-ins 320a-320d are active and all scan-outs 340a-340d are active. The multiplexers 330a-330c each select input 00. Scan data, SI1, SI2, SI3 and SI4 are respectively scanned into each scan chain 310a-310d. Likewise, scan out data, SO1, SO2, SO3, and SO4, are
- 15 used for the scan data. This process requires L clock cycles, the length of each scan chain.

- However, when in medium performance mode, only scan-ins 320d and 320b are active and only scan-outs 340c-340a are active. The multiplexers
- 20 330a-330c each select input 01. Two scan chains result, chain 310a+310b and scan chain 310c+310d. Scan data, SI2+SI1 is shifted into scan-in 320b and scan data SI4+SI3 is shifted into scan-in 320d. Likewise, scan out data SO1+SO2 is shifted out of scan-out 340a and scan data SO3+SO4 is shifted
- 25 out of scan-out 340c. In this mode, 5 pins are used for the scan data and this process requires 2L clock cycles, the length of each resultant scan chain.

When in low performance mode, only scan-in 320d is active and only scan-out 340a is active. The multiplexers 330a-330c each select input 10. One large scan chain results, chain 310a+310b+310c+310d. Scan data,

5 SI4+SI3+SI2+SI1, is shifted into scan-in 320d and likewise, scan out data SO1+SO2+SO3+SO4 is shifted out of scan-out 340a. In this mode, 3 pins are used for the scan data and this process requires 4L clock cycles, the length of each resultant scan chain.

10 With respect to Figure 4A and Figure 4B, the protocol unit 210 (Figure 3) determines the test sequence that is applicable for any given performance mode and implements that test sequence to perform the test. The test sequence includes which scan-in pins are active and which scan-out pins are active for each mode. The test sequence also includes which scan-in vectors (e.g., SIn)

15 are to be applied in which order to the active scan-ins. The test sequence also includes which scan out data vectors (e.g., SOn) are to be expected from which active scan-outs and in which order they are expected to be received. The test sequence can be stored as a computer program defining the different information for each performance mode, an example of this shown in Figure 7B

20 (described in more detail below). While the test sequence may change from one performance mode over another, it is appreciated that in accordance with the present invention, the actual scan-in data vectors, e.g., SIn, do not change. In effect, these scan-in data vectors become retargetable for different testers by way of the protocol unit 210 and the DFT logic added to each device under test

25 260.

Figure 5 illustrates an exemplary device under test 260c having reconfiguration logic for reconfiguring the number of functional input/outputs pins required for testing in a high performance mode versus a low performance mode. Figure 5 illustrates one manner in which functional inputs and outputs can be reconfigured into internal scan elements of the design. In high performance mode, all the functional input (FI) pins 430a-430e are active to receive five functional inputs. Multiplexers 450a-450e are controlled by control signal C3 367 to select their bottom inputs for high performance mode. These functional inputs are applied to the combinational logic 410 and five functional outputs F6-F10 are generated over 5 functional output pins 470a-470e. With respect to the functional input/output data, 10 pins are required to implement high performance mode. The control pin C3 is based on the mode selection signal which can be obtained from the scan data configuration (e.g., Figure 4A). That is to say, the scan chain implementation 310i and 310j can be based on the example of Figure 4A.

In low performance mode, none of the functional input (FI) pins 430a-430e are active. Instead, the functional input data are shifted into a series chain of clocked memory cells 440a-440e through a functional scan-in pin 420. Multiplexers 450a-450e are controlled by control signal C3 367 to select their top inputs for low performance mode. After shifting, these functional inputs are then applied to the combinational logic 410 and five functional outputs are generated and stored in series coupled clocked memory cells 460a-460e. In low performance mode, none of the 5 functional output pins 470a-470e are



active. Instead, when the functional inputs are shifted in, these functional outputs are shifted out over functional output scan-out pin 472. With respect to the functional input/output data, 2 pins are required to implement low performance mode, pin 420 and pin 472. The control pin C3 is based on the mode selection signal which can be obtained from the scan data configuration (e.g., Figure 4A). However, 5 extra clock signals are required because of the need to shift in/out the functional inputs and functional outputs. While the example of Figure 4A shows separate functional pins and scan pins, in accordance with an embodiment of the present invention, the solution for the two types can be merged for cases where the functional pin and scan pin are shared.

It is appreciated that the protocol unit 210 (Figure 3) is responsible for determining which functional input pins and which functional output pins are active and if functional input shifting and/or functional output shifting is required for any particular performance mode.

Figure 6 illustrates a flow diagram of steps 500 performed by an embodiment of the present invention for performing tester retargetable patterns.

Test application for high performance mode is similar to the conventional testing mode, therefore, the example shown in Figure 6 is for the application of high performance (high pin count) test vectors by a low performance (low pin count) tester. It is assumed that some low performance selection is made (manual, automatic, etc.) and that a low performance tester is connected to the device under test. At step 510, the low performance tester sets-up its scan-in

procedure and selects low performance protocol. The reconfiguration DFT circuit on-chip then configures the internal scan chains to implement long scan chains.

5           At step 520, scan-in is performed where the scan-in test vectors, SIn, are scanned into the device under test according to the selected test sequence as controlled by the protocol unit. In this example, the circuit of Figure 4A is referenced and both scan chains are connected together to act as one long scan chain. Also, according to the example of Figure 5, functional inputs are  
10       shifted into the functional input scan-in pin 420. At step 530, the scan data and functional inputs are applied to the circuit. At step 540 the outputs are computed. At step 550, the outputs are latched by the clock. At step 570, the scan-out is set-up where only the appropriate scan-out pins are known to be active.

15           At step 570, the scan-out data and the functional outputs are shifted out using the low performance test sequence. At step 580, the scanned out data is stored for a pass/fail determination by the low performance tester. Steps 510-580 can then be repeated for next scan vector. It should be noted that the scan-  
20       out operation (570) can be merged with the scan-in operation (520) of the adjacent test pattern. This overlapped operation is the typical way scan test patterns are applied.

          A pseudo code example is given with respect to Figure 7A and Figure  
25       7B. The pseudo code represents an example of the programming contained in

the protocol unit 210 for performing a test sequence for high performance mode and a test sequence for low performance mode. As shown in Figure 7A, the example device 260d contains two scan chains, "1" and "2," one reconfiguration mux, two scan-ins, SI1 and SI2, and two scan outs, SO1 and SO2. Not shown is a functional input shift register of the kind shown in Figure 5 and having a functional scan-in, funcIn, and a functional scan-out shift register with a functional scan-out, funcOut.

Figure 7B illustrates the resulting pseudo code 600 used by the protocol unit 210 for the example device of Figure 7A. The pseudo code (using IEEE 1450 and IEEE 1450.1 capabilities and syntax) represents the testing sequences where the scan operation of consecutive test patterns are overlapped and is on the tester side. Code section 610 is used for high performance mode and section 620 is used for the low performance mode. The test vectors, SIn, are all the length of the individual scan chains "1" and "2", e.g., L bits long. In high performance mode, the "Shift" command 640 indicates that scan-in pin, SI1, receives test data "SI1" and scan-in pin, SI2, receives test data "SI2." This scans in the two scan chains. Further indicated is that scan-out pin, SO1, takes the scan-out vector "SO1" and scan-out pin, SO2, takes the scan-out vector "SO2." While scan-in is performed, scan-out also occurs simultaneously. The shift command therefore shifts in two scan chains simultaneously and also, simultaneously, shifts out two scan chains in the time of L clock cycles. The "V" command 650 is the step where the functional pins are applied some stimulus and values are measured. It indicates that the functional inputs are applied as separate pins, e.g., the functional input pins receive the functional input signals

individually and that the functional output pins drive the functional output signals individually. The reconfiguration signal "many\_inputs" indicates a high performance tester and controls the reconfiguration multiplexers.

5           Code section 620 is used for low performance mode. In low performance mode, the "Shift" command 660 indicates that scan-in pin, SI1, receives test vector "SI1 SI2" which is the two vector concatenated together. This scans in the two scan chains as one chain of length 2L. Further, that scan-out pin, SO2, takes the scan-out vector "SO2 SO1" of length 2L. While scan-in is performed, scan-out also occurs simultaneously. The shift command therefore shifts in two vectors simultaneously and also, simultaneously, shifts out two vectors in the time of 2L clock cycles. Importantly, command 670 indicates that the functional inputs are also shifted into the funcIn pin and the functional outputs are shifted out from the funcOut pin. The "V" command 680 is the data capture step. The reconfiguration signal "few\_inputs" indicates a low performance tester. The following illustrates examples of the test vectors:

```
Do_one_test (     SI1=0000;   SI2=0101; )  
                                  SO1_p=0110;   SO2_p=1111; )]
```

where "\_p" with the name denotes the fact that the values are obtained from the previous test vector that is overlapped with the current test vector. It should be noted that the data for "func\_inputs," "func\_outputs" and "func\_outputs\_p" are not shown in the sample test vector.

The foregoing descriptions of specific embodiments of the present invention, a method and system for automatically retargeting test vectors developed for a high performance tester to be applied by either a low performance tester or a high performance tester based on a mode selector,

- 5 have been presented for purposes of illustration and description. They are not intended to be exhaustive or to limit the invention to the precise forms disclosed, and obviously many modifications and variations are possible in light of the above teaching. The embodiments were chosen and described in order best to explain the principles of the invention and its practical application, thereby to
- 10 enable others skilled in the art best to utilize the invention and various embodiments with various modifications as are suited to the particular use contemplated. It is intended that the scope of the invention be defined by the Claims appended hereto and their equivalents.